



Product Features

- 5.8G Microwave Motion Sensor
- 3-Step Sensor – ON-DIM-OFF
- Can be installed in the sensor location on the WL-WP50-3C with 2 screws and plug into the driver (requires no re-wiring)
- Adjustable Detection Area, Hold Time, Stand-by Period and Dim level, Lux Sensor (Requires the optional remote control to change the settings.)

Options:



Remote Control for Sensor Settings



Suitable for Installation in
WL-WP50-3C Wall Pack Light

Function	Default Setting
Stand-by Dim Level	30%
Hold Time	30s
Detection Area	100%
Stand-by Period	∞ (infinity)
Daylight Threshold	Disabled

Specification Overview



Model	Standby Power	Power Requirement	Fits Model	Dimensions
-------	---------------	-------------------	------------	------------

WL-WP-MMS	<0.5w	220~240VAC	WL-WP50-3C	60 x 25.5 x 27.2mm
-----------	-------	------------	------------	--------------------

WL-WP-RC	RF Remote Control (simplified) to suit WL-WP-MMS or WP70 Titan Wall Packs			
----------	---	--	--	--

SMD-MR-REMOTE	RF Remote Control (complex) to suit WL-WP-MMS, WP70 Titan Wall Packs and SMD-MR G2 Sensor Batterns			
---------------	--	--	--	--