



Dimmer Series – SMART Wi-Fi Dimmer Switch

Product Features

- Both manual and Wi-Fi Controlled dimmer
- Available in Rotary or Push Button
- Dimmer with push ON/OFF switch
- S-mart lighting control powered by TUYA
- Works with 2.4GHz enabled W-Fi router
- Compatible with Alexa and Google Home
- Soft Start
- Fits most standard wall plates (excludes Clipsal Iconic)
- No Neutral Required
- Load: Min 5w / Max 250w
- Programmable Min/Max dimming levels



Options:



Black Knob
(suits rotary only)



Load Correction Device



Specification Overview

Model	Type	Dimming Mode	Size	Max Load	Min Load	Comments
DIM-SMART-R	Rotary	Trailing Edge	59.1 x 22.5 x 40mm	250w	5w	Wi-Fi and wall-controlled dimming
DIM-SMART-P	Push	Trailing Edge	47.2 x 22.5 x 40mm	250w	5w	Wi-Fi and wall-controlled dimming
DIM-SMART-R-BK	Matt Black Knob to suit DIM-SMART-R Dimmer					
DIM-LCD	Load Correction Device Used to reduce dimming issues/flickering					