

Outdoor Wall Light
30w Bunker Emergency Pack



Product Features

- Suits WL-BH30-3C-B or WL-BH30-3C-W
- Complete swap out LED board with Emergency Pack assembled
- Includes test switch and indicator light
- Optional Motion Sensor or Dusk-to-dawn PE cell can be installed

Options:



Microwave Sensor
Model: WL-BH-MMS2



Dusk-to-dawn sensor
Model: WL-BH-PE



Model	Power	Lumens	CCT	Dimension	Weight
WL-BH30-EP	30w	2463~2722lm	3000K/4000K/5000K	Ø285 x 30mm	550g

Specification			
CCT	3000K/4000K/5000K	Lifespan	>40,000 hours
Efficacy	>82lm/w	Operation Temperature	-25 °C to +45°C
CRI (%)	≥80	Emergency Power	4w
Beam Angle	120°	Emergency Run-Time	180 minutes
Power Input	220~240VAC	Battery	LifePO4 6.4v 1500mAH
Dimmable	No	Warranty	5 Years 3 Years Battery

Specifications are subject to change without notice