

Product Specification



Bunker Light Accessories

PE Photocell Sensor



Product Features

- Dusk-to-Dawn switching
- Installed in the sensor cut-out area of the approved list below (requires minimal re-wiring)
- Multiple lux level settings
- Sensor distinguishes between artificial and natural light



Suitable for Installation in

WL-BH16-3C Series Bunker Lights

WL-BH20-3C Series Bunker Lights

WL-BH30-3C Series Bunker Lights

WL-WP50-3C Wall Pack Light



Specification Overview

Model	Standby Power	Input	Fits Models	Dimensions
WL-BH20-PE	<0.5w	220~240VAC	WL-BH16, WL-BH20, WL-BH30, WL-WP50	55.5 x 36 x 22mm



5627

Product Specification



Bunker Light Accessories

PE Photocell Sensor

Switch to Excellence

Model	Power Requirement	Fits Models	Dimension
WL-BH20-PE	220~240VAC	WL-BH16, WL-BH20, WL-BH30, WL-WP50	55.5 x 36 x 22mm

Specification			Dimensions
Power Input	220~240VAC	Operation Temperature	-25 °C to +60°C
No Load Power	≤ 0.5W	Housing Colour	White
Max Load	≤ 800W (resistive) ≤ 400W (LED)		
Protection Rating	IP20	Warranty	5 Years

Dip Switch Settings (ON/OFF Value)

	1	2	3	4	ON	OFF
I	ON	ON	ON	ON	5Lux	25Lux
II	ON	ON	ON	-	10Lux	50Lux
III	ON	ON	-	ON	25Lux	75Lux
IV	ON	ON	-	-	50Lux	100Lux
V	ON	-	ON	-	100Lux	200Lux
VI	ON	-	-	-	150Lux	300Lux
VII	-	ON	-	-	200Lux	400Lux
VIII	-	-	-	-	Disable	

Recommended setting
for dusk to dawn

Working Mode: When the light reaches the set value, the light will turn ON/OFF after an 8 second delay

Specifications are subject to change without notice