

Bunker Light Installation Instructions

Safety Instructions

To ensure correct function and safety, please read and follow all instructions carefully before using the product:

1. Turn off power supply before installation or before doing any maintenance work.
2. Do not exceed the nominal supply voltage or amperage ratings.
3. All wiring and installation of the light fitting must adhere to local and national wiring rules and be completed by a qualified electrician.
4. Take care not to pull any electrical wires during unpacking as this may damage the connection.
5. All holes, cable entry points must be sealed with neutral cure silicone to retain the IP rating of this product.
6. Lay out all the components on a smooth surface and make sure there are no components missing before assembling.
7. To avoid injury or damage to the fitting, please ensure that power leads and screws are secure before connecting the power.
8. Please keep instructions for future reference.

Installation Procedure

WARNING

1. Switch off before installation.
2. Switch on only after complete installation and examination of the circuit.
3. Professional electrician for installation and maintenance only.



**Turn Off
Power Supply**


Step 1

Take the light and accessory pack from the box




Step 2

Remove the security screws and take off the cover




Step 3

Remove the LED Board and disconnect from the driver
Handle the LED board by the edges so no damage occurs to the LED board.




Step 4

Mount the housing onto the wall or ceiling and tighten screws ensuring all screw points and cable entry holes are sealed with neutral cure silicone sealant to retain the IP rating and connect the AC cables to the terminal block.



Step 5

Re-connect the LED board and front lens cover ensuring that the rubber seal is in place and the Cover is secured properly to ensure a complete Seal. Now you can switch on the light



Need more help?

Should you require more information or have any questions relating to this product please do not hesitate to contact S-Tech on 08 9330 8485

www.s-tech.com.au