



Dimming Cable Colour Codes

The high bay light is supplied with a 0-10V dimmable driver as standard.

To use the dimming function, you can use a 0-10V rotary dimmer wired as per the dimmer manufacturer instructions to the DIM+ and DIM- as marked on the additional dimming cable that is connected to the driver.

Alternatively the dimming is wired as part of the microwave sensor option for this light.

Type A

Purple DIM+ 

Grey DIM- 

Type B

Purple DIM+ 

Grey DIM- 

Pink Vaux+ 

Pink is not required for our supplied sensors, please ensure this remains covered by the protective boot.

All dimming cables if not used must have the supplied protective boots fitted to stop any shorting of cables which will damage the driver

Please read these instructions carefully in full prior to carrying out the installation.

IMPORTANT SAFETY ISSUES

- This product must be installed by a qualified electrician according to AS/NZS 3000.
- Ensure that the AC power is disconnected at the switchboard and test to ensure that there is no power on the circuit prior to starting installation.
- This product is rated to IP65 and is suitable for damp environments.
- Modification of this product will void any warranty.
- When cleaning or replacing the light, please ensure the power is off and the light is completely cooled down. Cleaning can be done using a soft cloth and PH neutral detergent.

INSTALLATION INSTRUCTIONS

- Disconnect the power at the switchboard.
- Ensure an AC socket or outdoor junction box is installed within 2100mm of the lights position.
- Default power setting is 200w, to change the setting remove grommet from the side of the driver and change dip switch setting as per the chart below. The rubber grommet **MUST** be re-installed to ensure IP and dust rating for this driver. Warranty is void if this is missing.
- Mount the light as required through the eye bolt or using the optional surface mount bracket.
- For 0-10V dimming, please refer to back page of these instructions.
- Plug in the AC cable into the surface mount socket or terminate into the junction box.
- Check all connections are correct.
- Turn power back on at the switchboard and test the lights operation.

WATT Select Settings

